

HYBRID MULTI BAND ANTENNA ARRAY

Model HBSA-M65-19R010-63



Hybrid Multi Band Antenna Array

Benefits

Multi band applications – 700 MHz, SMR 800 MHz, Cellular 850 MHz, PCS 1900 MHz, AWS 1710/2155 MHz, WCS 2305/2360 MHz

Enables efficient evolution of wireless networks

Increase site capacity through higher order sectorization

Avoid carrier-adds and building of new capacity sites

Boosts data throughput by lowering interference

Unique hybrid phased array design, maximizes coverage in a standard tri-sector cell plan

Provides remote control of electrical downtilt of antenna for easier optimization The CCI RET Series Hybrid Multi Band Antenna Array is an industry first LTE ready hybrid phased array that supports multiple sectors (one low band, two high bands) from a single antenna and provides capability for 700 MHz , SMR 800 MHz, Cellular 850 MHz, PCS 1900 MHz, AWS 1710/2155 MHz and WCS 2300 MHz coverage in a single, compact enclosure. Our unique hybrid design, 6 ft high and 12.9 inches wide, combining standard 65° and patented bi-sector technology, maximizes coverage in a standard tri-sector cell plan, provides optimized overlap between pairs of asymmetric beams, lowers soft handover losses in UMTS/HSPA+ and CDMA/EVDO systems, and minimizes interference between sectors. Such an approach enhances data transfer rates within UMTS/LTE and EVDO network sectors and addresses "hotspots" in mobile wireless operator networks for SMR, GSM, CDMA, UMTS and LTE technologies.

The remote electrical tilt (RET) Series Multi Band Hybrid Bi-Sector Array enables operators to remotely control the electrical down-tilt of the antenna in the field with sealed AISG compliant RET actuators. The CCI RET system is designed to meet the reliability, flexibility and efficiency requirements in a wide range of environments. The RET actuators are fully AISG compliant, software upgradeable, daisy chaining capable and fully weather resistant. The remote electrical capability allows independent adjustment of sub-beams for easier optimization.

The single panel design of the hybrid phased array offers the opportunity to reduce antenna count and directly replaces an existing 65° antenna. The new coverage that matches the existing footprint minimizes the need for optimization and adjacent site changes, and allows for significant CAPEX and OPEX cost savings.

All CCI antennas are manufactured under ISO 9001.

Features

- Unique hybrid phase array combining standard 65° over a frequency range of (698-894 MHz) and asymmetric 33° Bi-Sector array over a frequency range of (1710-2360 MHz), optimized to match existing cloverleaf (65°) deployments.
- Slim and low weight single panel design supporting 3 beams without mount changes
- Independent adjustable beams provide unmatched optimization flexibility
- Separate Low-band and High-band ports
- ♦ 3GPP/AISG 2.0 compliant
- Daisy chaining capability
- Software upgradeable
- Rugged, weather resistant and highly reliable internal design

Applications

- Upgrade of data-throughput or capacity constrained sites
- Spectrum limited markets
- Deferral of CDMA/EVDO or UMTS//HSPA+ carrier adds
 - Spectrum clearing and refarming



Extending Wireless Performance



www.cciproducts.com



HYBRID MULTI BAND ANTENNA ARRAY


Model HBSA-M65-19R010-63

HBSA-M65 Antenna Array Electrical Specifications

	2 X Low Band Ports which cover the full range from 698-894 MHz		4 X High Band Ports which cover the full range from 1710-2360 MHz			
Frequency Range	698-806 MHz	824-894 MHz	1850-1990 MHz		/2110-2155 Hz	2305-2360 MHz
Gain	14.5 dBi	15.2 dBi	18.3 dBi	17.3 dBi	19.1 dBi	19.2 dBi
Azimuth Beamwidth (-3dB)	68°	65°	33°	36° 🔶 🔪	28.5°	27°
Elevation Beamwidth (-3dB)	12.0°	10.5°	5.7°	6.2°	5.1°	4.5°
Electrical Downtilt	2° to 10°	2° to 10°	0° to 8°	0° to 8°	0° to 8°	0° to 8°
Elevation Sidelobes (1st Upper)	< -18 dB	< -18 dB	< -18 dB	< -18 dB	< -18 dB	< -16 dB
Front-to-Back Ratio @180°	> 30 dB	> 30 dB	> 30 dB	> 30 dB	> 30 dB	> 30 dB
Front-to-Back Ratio over ± 20°	> 25 dB	> 25 dB	> 30 dB	> 30 dB	> 30 dB	> 30 dB
Cross-Polar Discrimination (at Peak) > 25 dB	> 25 dB	> 22 dB	> 22 dB	> 22 dB	> 20 dB
Cross-Polar Discrimination (at ± 30°) > 22 dB	> 20 dB	> 20 dB	>20 dB	> 20 dB	> 19 dB
Cross-Polar Port-to-Port Isolation	> 25 dB	> 25 dB	> 25 dB	> 25 dB	> 25 dB	> 25 dB
VSWR	< 1.5:1	< 1.5:1	< 1.5:1	< 1.5:1	< 1.5:1	< 1.5:1
Passive Intermodulation (2x20W)	≤ -150dBc	≤ -150dBc 📈	≦ -150dBc	≤ -150dBc	≤ -150dBc	≤ -150dBc
Input Power	500 Watts CW	500 Watts CW	300 Watts CW	300 Watts CW	300 Watts CW	300 Watts CW
Polarization	Dual Pol 45°	Dual Pol 45°	Dual Pol 45°	Dual Pol 45°	Dual Pol 45°	Dual Pol 45°
Input Impedance	50 Ohms	50 Ohms	50 Ohms	50 Ohms	50 Ohms	50 Ohms
Lightning Protection	DC Ground	DC Ground	DC Ground	DC Ground	DC Ground	DC Ground
Mechanical Specifications						
Dimensions (LxWxD) 7	2.0 x 12.9 x 9.0 incl	nes (1828 x 328 x 2	29 mm)		Ι.	l.
Survival Wind Speed >	125 mph (> 193 km	n/hr)				Second Second
Front Wind Load 2	21 lbs (982 N) @ 10	00 mph (161 kph)				
Side Wind Load 1	65 lbs (735 N) @ 10	00 mph (161 kph)				
Equivalent Flat Plate Area 8	$.6 \text{ft}^2 (0.8 \text{m}^2)$				• 🔘	
Weight (without Mounting) 5	7.0 lbs (26 kg)					
	.0 lbs (2.3 kg)					
	; 7-16 DIN female					/
	-5 inches (5-12 cm)			K X		
Antenna Patterns*		Rear View		Bottom View		

Antenna Patterns*

Rear View



*Typical antenna patterns. For detail information on antenna pattern, please contact us at info@cciproducts.com. All specifications are subject to change without notice.

www.cciproducts.com

USA: 89 Leuning Street, South Hackensack, NJ 07606 Telephone: 201-342-3338 Canada: 411 Legget Drive, Suite 104, Ottawa, ON Canada K2K 3C9 Telephone: 613-591-6696



HYBRID MULTI BAND ANTENNA ARRAY

Electrical Specification

Model HBSA-M65-19R010-63

Ordering Information:

HBSA-M65-19R010-63	Antenna (6'), Hybrid Bi-Sector Array, Multi-band (700/800/850, and 1710/2360), with Factory Installed Actuators (3)	MBK-01 Top Mounting Bracket	
HBSA-M65-19R010-63-K	Complete Kit with Antenna, Factory Installed Actuators (3) and MBK-01 Mounting Bracket		
BSA-RET200	RET Actuator		See Car
MBK-01	Mounting Bracket (Top & Bottom) with 0° through 10° Mechanical tilt Adjust- ment: See Installation Guide 50-000036-01 for Details: Weight 13.6 Lbs. (6.2 kg)	MBK-01 Bottom Mounting Bracket	

RET [Remote Electrical Tilt] System


General Specification

· · · · · · · · · · · · · · · · · · ·			
Part Number	BSA-RET200	Interfacé Signal	Data dc
Protocols	AISG 2.0	Input Voltage Range	10-30 Vdc
RET Type (Reference AISG 1.1)	Туре 1	Current consumption during tilting	120mA at Vin = 24V
Adjustment Cycles	>10,000 cycles	Current consumption idle	55mA at Vin=24V
Tilt Accuracy	±0.1°	Hardware Interface	AISG - RS 485 A/B
Temperature Range	-40°C +70°C	Input Connector	1x8-pin Daisy Chain
		Output Connector	1x8-pin Daisy Chain

Mechanical Specification and Dimensions

Housing Material	
Dimensions (H x W x D)	
Weight	

ASA / ABS / Aluminum 8 x 5 x 2 inches (213 x 135 x 51 mm) 1.5 lbs (0.68 kg)





x8-pin Daisy Chain In Male x8-pin Daisy Chain Out Female

Standards Compliance

Safety	EN 60950-1, UL 60950-1
Emission	EN 55022
Immunity	EN 55024
Environmental	IEC 60068-2-1, IEC 60068-2-2, IEC 60068-2-5, IEC 60068-2-6, IEC 60068-2-11, IEC 60068-2-14, IEC 60068-2-18, IEC 60068-2-27, IEC 60068-2-29, IEC 60068-2-30, IEC 60068-2-52, IEC 60068-2 -64, GR-63-CORE 4.3.1, EN60529 IP24

Regulatory Certification

AISG, FCC Part 15 Class B, CE, CSA US

USA: 89 Leuning Street, South Hackensack, NJ 07606 Telephone: 201-342-3338, FAX: 201-342-3339 Canada: 11 Hines Road, Suite 200, Ottawa, ON Canada K2K 2X1 Telephone: 613-591-6696, FAX: 613-591-